Adapt ADK-200 iPAD/iPhone 4 Bluetooth Keyboard Manual

Packing Includes:

1 Adapt ADK-200 iPAD/iPhone 4 Bluetooth keyboard
2 IPAD/IPHONE 4 case (optional)
3 ADK-200 English Manual
4 USB charging cable for use with the ADK-200 Mini USB keyboard version (The Apple 30-pins version does not have a charging cable included, you can use the iPAD/iPhone 4's original Cable)





Bluetooth Keyboard

Product Features:

1 Broadcom 2042 main control chip with Bluetooth 2.0 interface.
2 ADK-200 is using the industries leadings Bluetooth solution: WIDCOMM BTW Bluetooth software.
3 Specially design for IPAD/IPHONE 4i/iPhone 4 with multimedia control function keys
4 Built-in power management software
5 Silent key design
6 It is splashwaterproof and dustproof
7 Works also with PC via HID profile
8 Working temperature :-20℃-55℃ humidity:20%-50%
9 Built-in lithium battery

Specifications :

1 Standard: Bluetooth V2.0
2 Working distance: upto 10 meters
3 Modulation system: FHSS 2.4G
4 Transmitting power: Class 2
5 Operating voltage: 3.0-5.0
6 Work current: <5.0MAh
7 Standby current: 2.5MAh
8 Sleeping current: <200UA
9 Charging current:> 100MAh
10 Standby time: 100days
11 Maximum working time: 25 days
12 Uninterrupted working time: 90 hours
13 Charging time: 4-4.5 hours
14 Li-ion battery capacity: 430MAh

15 Lithium battery life: upto 3 years
16 Lithium battery specifications: 4.5 * 24 * 47MM
17 Key strength: 80 ± 10g
18 Key life: upto 500 million strokes
19 Operating temperature: -20 - +55 Degrees Celcius
20 Storage temperature: -40 - +70 Degrees Celcius

Installation of the ADK-200 Bluetooth Keyboard

1 How to connect the ADK-200 Bluetooth Keyboard to you IPAD/IPHONE 4.

Step 1: Find the keyboard

(1) Switch the toggle switch to "ON" , the power light and Bluetooth light will light up for 3 seconds. After this it will turn of and the keyboard is in operation mode.
(2) Press the connect button ,the Bluetooth light will be flashing and the Power light will be on, the keyboard is now in pairing mode.



(3) Click on the "Setting" button on your iPAD/iPhone 4's home screen, then choose "General" and select "Bluetooth". Turn the Bluetooth switch to "ON" and the iPAD/iPhone 4 will start looking for Bluetooth devices.

Step 2: Enter the password and connect



iPAD is in searching mode and will find the Wireless Bluetooth Keyboard

A pop-up field with the password shows, type this password on the ADK-200 and press "ENTER"

The iPAD/iPhone 4 will list the keyboard as "Bluetooth Wireless Keyboard", click on this and it will prompt you to type the passkey onto the ADK-200 keyboard. Type the password on the keyboard and press "ENTER". The "Bluetooth Wireless Keyboard status will be "Connected" and you can start using the keyboard.

Step 3: Connect successfully, the keyboard is in working mode



Connect successfully

The keyboard is working now

After successful connection, the keyboard power light will keep burning. If you stop using the keyboard do not forget to switch it off.

Charge:

If the keyboard will run out of power the power LED will start to flash indicating it is time to charge the keyboard.

Charging procedure as follows :

1. Connect the Micro USB cable or iPAD/iPhone 4 cable (depending on the model) to the charging interface. The keyboard can charge both during use and in off function. We advise however to always charge the keyboard when it is turned off, this will increase the lifetime of the battery. We advise also to only charge the ADK-200 after the red power light starts to blink, again to save the lifetime of your battery.



2 During charging the "Charge indicator light" will burn red, when the keyboard is fully charged it will turn off (charging time: 4.5 hours.)

Storage:

1 When you are finished using your keyboard do not forget to switch it off to extend the battery life.
2 When you do not intend to use your keyboard for a longer period, try to store it with at least half a battery load, this will extend the life of the Li-ion battery.

Note: When storing the keyboard, do not fold it!

Attentions:

1 Keep the keyboard away from sharp objects.
2 Do not put heavy object on the keyboard
3 Keep away from oil or any other chemical liquids.
4 Make sure the keys are not pressed when you store your keyboard
5 The keyboard can be washed with water and a mild detergent, or alcohol

Sleep Mode:
The ADK-200 will go into sleep mode after not being used for 15 minutes. In order to get the keyboard out of sleep mode, simply press any key on the keyboard and after 3 seconds it will work again.

TROUBLESHOOT GUIDE:

1 If you are unable to connect the Bluetooth Keyboard to the computer, please follow the steps below:

(1) Before you install your Bluetooth Keyboard, please make sure the Bluetooth is turned on
(2) Press and release the connect button on the top of Bluetooth Keyboard. The Bluetooth LED will flash to show it is able to pair with your iPAD/iPhone 4/iPhone 4
(3) Make sure that the keyboard is within the effective range, less then 10 meters (or around 300 feet)
(4) If you have to many Bluetooth devices paired with your iPAD/iPhone 4/iPhone 4, try to reduce the number of connected devices
(5) Check if the power LED is blue and not blinking red
(6) Make sure your iPAD/iPhone 4 is functioning properly

2 IMPORTANT NOTE:
After switching of the keyboard power and Bluetooth from you iPAD/iPhone 4, the keyboard can automatically reconnect without re-entering the pairing code. To do this first turn on the keyboard and after that switch on the Bluetooth from your iPAD/iPhone 4. Then wait till the Bluetooth indicator LED from your keyboard turns off and then press the ENTER key on your ADK-200 keyboard. Note that it might take over 30 seconds before the keyboard and iPAD/iPhone 4 reconnect, please keep that in mind.

If you do not use the keyboard for 15 minutes it will enter a sleep mode. When you want to use it again, press a key and wait till ADK-200 wakes up again

Apple function keys:

The ADK-200 has special function keys to control the multimedia functions of your iPAD/iPhone 4. Below we have listed them for you.

F5 — The F5 function key will pop-up the iPAD/iPhone 4 onscreen keyboard

F6 — The F6 function key will open the iPAD/iPhone 4 search function

F7 — The F7 function key will select the previous song in the iPAD/iPhone 4 iPOD menu

F8 — The F8 function key will start playing the selected song in the iPAD/iPhone 4 iPOD menu, press it again and it will pause, press it again and it will start to play again

F9 — The F9 function key will select the next song in the iPAD/iPhone 4 iPOD menu

F10 — The F10 function key will mute the song (it will keep playing in the background)

F11 — The F11 function key will decrease the volume

F12 — The F12 function key will increase the volume

This key will return you to the HOME screen from the iPAD/iPhone 4. Press it again and it will switch to the search function. Press it once more and it will return you to the "HOME" screen.

Federal Communication Commission Interference Statement

This equipment has been tested and found to comply with the limits for a Class B digital device.
Pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if no installed and used in accordance with the instructions, may cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one of the following measures:

- Reorient or relocate the receiving antenna
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

FCC Caution: Any change or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

IMPORTANT NOTE:
FCC Radiation Exposure Statement:
1. This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. End users must follow the specific operating instructions for satisfying RF exposure compliance.
2. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

MADE IN CHINA

Adapt ADK-200 iPAD/iPhone 4 Bluetooth Keyboard Manual