Q9 2-in-1 Bluetooth 5.3 Wireless Transmitter & Receiver with MP3 Player



Specifications

Operation in receiving mode

- 1. Press and hold the [green telephone receiver] key to turn on the device. It is in the receiving mode by default and "RX" indicator flashes.
- 2. Insert one end of the audio cable into the adapter AUX interface, and the other end into the audio output interface of speakers.
- 3. Open the Phone Settings Bluetooth Search for Bluetooth devices, select "BT-TX RX" in the Bluetooth list to pair. After successful pairing, the "RX" indicator light will remain on. Turn on the mobile music app to play songs, and the mobile music can be played through devices such as speakers.

Operation in transmission mode

- 1. In RX receiving mode, Short presses the "M" button to enter transmission mode, and the "TX" indicator flashes.
- 2. Insert one end of the audio cable into the adapter audio interface, and the other end into the audio output interface of computers and televisions.
- 3. Turn on the Bluetooth devices that need to be connected (such as Bluetooth headphones, Bluetooth speakers, etc.) to enter pairing mode and place them within a 10 meter range.
- 4. This product will automatically search and match nearby Bluetooth devices (such as Bluetooth headphones, Bluetooth speakers, etc.) and automatically connect. After successful connection, the "TX" indicator light is always on.

Operation of ambient light

The ambient light automatically fades the color of the light when the device is turned on. Click the [black light bulb] button to turn the light into monochrome, and then click the [black light bulb] button seven times to turn off the ambient light.

Low battery warning

When the battery is low during use, a voice warning will be given, and it will automatically shut down when the battery is low.

Screen indicator

RX: represents receiving mode, blue light flashing (waiting for pairing), blue light always on (successful pairing).

TX: represents the launch mode, red light flashing (waiting for pairing), red light always on (successful pairing).

Charging: TX red light remains on during charging and goes off when fully charged.

Key operation method

[~]

Click: Play/pause/ answer /hang up

Double click: Call back

Long press: Turn on/off/reject

M - Button - Click: TX/RX mode switching



Click: Switch light color

[144]

Click: Previous song Long press: Volume -

[**|**

Click: Next song

Long press: Volume +

Technical parameters

- Bluetooth version V5.3
- Bluetooth transmitting power 7dBm
- Output impedance 32Ω
- Frequency response 20-20Khz
- Signal-to-noise ratio 90db
- Microphone sensitivity -42db
- Bluetooth receiving effective distance ≥10M
- Effective range of FM transmission ≥2M
- Input parameter 5V/2.1A
- Battery capacity 180mAh
- Charge time About 2 hours
- Listening time About 4-6 hours

Notes

- 1. Please charge the device in a safe environment. After fully charging, please disconnect the device from the charging cable to avoid damage to the battery inside the device due to prolonged charging.
- 2. This product is an audio transmission device and does not support image/file transmission.
- 3. Please do not forcefully dismantle, strongly impact or forcefully squeeze this product.
- 4. Do not throw this product into the fire.
- 5. When not in use for a long time, it is recommended to turn off this product.
- 6. Please store this product in a dry, moist, and corrosive environment. 7. Please take good care of children to ensure that they do not play with the product.