

User manual for Multifunctional Wireless Charging Station with Clock C100



Specifications

- Model: C100
- Input: DC 9V-2A/3A, QC3.0
- Smartphone output: 15W/10W/7,5W/5W
- Apple Watch output: 2W
- AirPods output: 3W
- Charging distance: up to 8mm
- Charging efficiency: up to 73%
- Clock battery: 2032
- Dimensions: 220mm x 150mm x 100mm
- Weight: 220g



1. Wireless coil center
2. Wireless coil center
3. For AirPods 2/AirPods Pro
4. For Apple Watch
5. Usage of the vertical charger (blue for charging, flashing red for a foreign object or high-temperature detection)
6. Usage of the AirPods charger (blue for charging, flashing red for a foreign object or high-temperature detection)
7. Time display
8. Reset key

Setting the time

- Long-press the + button (the time will start flashing).
- Short-press the M button to switch between the year, day and time. Adjust the year, month, day, and time by pressing the + or - buttons.
- "24 Hr" will start flashing, so short-press the + button to choose between 24-hour or 12-hour display.
- Short-press the M button to choose between display modes: dP-1 (only time) or dP-2 (time and date).
- Long-press the M button to turn off the display, short-press the M button again to turn it on.
- Short-press the + button to adjust the brightness